

Zaślepka D-Life antracytowa

Schneider Electric Merten System Design blind cover plate MTN4075-6034 is a carrying frame with central plate in color anthracite. This blind cover plate belongs to System Design aesthetic group. The device's fixing mode is by screw. Its matching mounting box can be recessed into the surface of the wall with flush type. It is 71 mm in width, 17 mm in height. The varnished surface treatment helps deliver a clear transparent hard protection. The blind cover plate is made of ABS (acrylonitrile butadiene-styrene), making it as resistant as possible. Besides it is halogen free halogen free, which is good for your health. Merten System Design is a modern modular switch range providing a wide range of inserts for a conventional installation with switches, socket-outlets, dimmers, USB chargers, and RJ45 connectors.



Informacje ogólne

GTIN/EAN	3606480889592
Alt. ID produktu	MTN4075-6034
Nazwa producenta	SCHNEIDER ELECTRIC
ID produktu wg producenta	MTN4075-6034
Seria produktu	Seria łączników i gniazd Merten
PKWiU	27.33.13.0
Kod celny	85389099

Opis ETIM

Klasa	Element (mechanizm/plakietka) techniki komunikacyjnej (EC000018)
Grupa	Elementy instalacyjne i podłączeniowe (EG000013)
Konfiguracja elementów	Element podstawowy z centralną plakietką osłonową
Zastosowanie	Zaślepka
Uchwyt transportowy	Tak
Z ochroną przeciwpyłową	Nie
Z pokrywą uchylną	Nie
Kierunek wylotu	Prosty
Oznaczenie/etykieta	Bez oznaczenia
Z nadrukiem	Nie
Sposób montażu	Montaż podtynkowy
Materiał	Tworzywo sztuczne
Gatunek materiału	Tworzywo termoplastyczne

Bezhalogenowe	Tak
Zabezpieczenie powierzchni	Lakierowanie
Wykończenie powierzchni	Matowy
Kolor	Antracyt
Numer RAL (zbliżony)	Brak informacji
Przezroczysty	Nie
Sposób mocowania	Montaż śrubowy
Liczba modułów (dla systemów modułowych)	1
Z gniazdami/złączami	Nie
Do liczby gniazd/złączy	0
Z odciążeniem naprężeń	Nie
Gniazda ekranowane	Nie
Obudowa ekranowana	Nie
Kostka łączeniowa	Nie
Stopień ochrony (IP)	IP20
Szerokość osprzętu	73 mm
Wysokość osprzętu	73 mm
Głębokość osprzętu	31 mm
Min. głębokość puszki montażowej	Brak informacji